The Hong Kong University of Science and Technology Cisco Unified IP Phone 8841 User Quick Reference

- 1) Message Waiting Indicator
- 2) Display
- 3) Line Buttons
- 4) Soft Keys
- 5) Navigation Keys
- 6) Release
- 7) **Hold**
- 8) Conference
- 9) Transfer
- 10) Handsfree Speaker
- 11) Audio Mute
- 12) Headset
- 13) Dial Pad
- 14) Volume Control
- 15) Contacts
- 16) Settings / Applications
- 17) Voicemail
- 18) **Back**
- 19) Receiver



Service Features	Access				
Internal Call	Dial 4 digits extension no.				
External Call	Dial 9 + tel. no.				
Speakerphone (Handsfree Speaker) On	Press (Green Light is on)				
• Off	Press again				
Audio Mute On	During a call, press (Red Light is on)				
• Off	Press Z again				
Video Mute On Off	Turn the camera shutter clockwise to start the video Turn the camera shutter counterclockwise to stop the video				
Redial (redial last dialed number)	Press { Redial }				
Call Hold • put a line on hold	Press (the 1 st line button flashes green)				
• reconnect the call	Press { Resume } or				
Call Transfer transfer	+ Ext. No. / 9 + Tel No. + /{ Transfer }				
• reconnect (if the line is no answer / busy)	Press { Cancel } + { Resume }				
Conference (8 Parties Audio/Video Calls) • set up	+ Ext. No. / 9 + Tel. No. + /{ Conference }				
• reconnect (if the line is no answer / busy)	Press { Cancel } + { Resume }				
Call Pickup • group pickup	Dial *8				
Call Park (Hold a call and retrieve it at another phone) • park a call	During a call, transfer the call to { 2755 } (A voice prompts a 4-digit Park No.)				
reconnect a parked call	Enter the Park No. at another phone				
Call Forward • set up (all calls)	Press { Fwd All } + Ext. No. (Screen shows & "To XXXX")				
• cancel	Press { Fwd Off }				

Service Features	Access
Access Voicemail System (Note: The new voicemail system number is 8181	When having voicemail, Message Waiting Indicator is on (Red).
instead of 8000) • internal access	Press or dial 8181, enter pin no.#
external access	Dial 2358 8181, enter 4-digit extension no. & pin no.#
Call Log (total stores up to 150 records)	2 in 2000 0101, oner i digit onension noi et più noi:
dial from call log	Settings / Applications
	+ (1. Recents) + select a call log record + Press { All Calls } or { Missed Call }
	Received , Placed - , Missed - + { More } + { Edit Dial } to edit the displayed number if necessary + { Call } / lift the handset to start calling
Personal Directory (Personal Phonebook)	
Open Personal Phonebook	+ (4. Personal Phonebook) + { Select }
	+ (2. Phone Directory) + { Submit }
a goorch for an antwi	Use the Navigation bar and button to scroll and select Open Personal Phonebook + { Search }
search for an entry	+ enter Search Criteria + { Submit }
dial from entry	Search for an entry + { Select } + { Dial }
Speed Dial	Press the session button next to the name
Review Call History	Press the button next to or , select the number to edit and dial
	Launch a web browser, & go to https://frsip.ust.hk/
Telephone Web Portal	Login using 4-digit telephone extension no. and telephone web portal password
Contrast	Press + (2. Settings)
	+ (3. Brightness) + to adjust + { Save } to confirm
Ring Tone	Press + (2. Settings)
	+ (2. Ring Tone) + to change +
	select Ring Tone + { Play } to listen / { Set } to use
Volume	
adjust the handset, headset and speaker volume	When handset, headset or speaker is in use (off hook), press:
adjust the ringer volume	When handset, headset and speaker is not in use (on hook), press:

	Buttons / Keys										
•	Ţ.		4		0	<u> </u>	₩	u .	+	X	
Handsfree Speaker	Audio Mute	Hold	Transfer	Conference	Navigation (Up, Select, Down)	Voicemail	Settings / Application	Contacts	Volume Control	Forwarded icon	{} Softkey