The Hong Kong University of Science and Technology Cisco Unified IP Phone 7841 User Quick Reference

- 1) Message Waiting Indicator
- 2) Line Buttons
- 3) Display
- 4) Soft Keys
- 5) Navigation Keys
- 6) Hold
- 7) Conference
- 8) Transfer
- 9) Handsfree Speaker
- 10) Headset
- 11) Audio Mute
- 12) Dial Pad
- 13) Volume Control
- 14) Contacts
- 15) Settings / Applications
- 16) Voicemail
- 17) Receiver



Service Features	Access					
Internal Call	Dial 4 digits extension no.					
External Call	Dial 9 + tel. no.					
Speakerphone (Handsfree Speaker) On	Press (Green Light is on)					
• Off	Press again					
Audio Mute On	During a call, press (Red Light is on)					
• Off	Press again					
Redial (redial last dialed number)	Press { Redial }					
Call Hold • put a line on hold	Press (the 1 st line button flashes green)					
• reconnect the call	Press { Resume } or					
Call Transfer transfer	+ Ext. No. / 9 + Tel No. + /{ Transfer }					
• reconnect (if the line is no answer / busy)	Press { Cancel } + { Resume }					
Conference (3 Parties Audio/Video Calls) • set up	+ Ext. No. / 9 + Tel. No. + (Conference)					
• reconnect (if the line is no answer / busy)	Press { Cancel } + { Resume }					
Call Pickup • group pickup	Dial *8					
Call Park (Hold a call and retrieve it at another phone) • park a call	During a call, transfer the call to { 2755 } (A voice prompts a 4-digit Park No.)					
reconnect a parked call	Enter the Park No. at another phone					
Call Forward • set up (all calls)	Press { Fwd All } + Ext. No. (Screen shows & "To XXXX")					
• cancel	Press { Fwd Off }					

Service Features	Access					
Access Voicemail System						
(Note: The new voicemail system number is 818 instead of 8000)	When having voicemail, Message Waiting Indicator is on (Red).					
internal access	Press or dial 8181, enter pin no.#					
external access	Dial 2358 8181, enter 4-digit extension no. & pin no.#					
Call Log (total stores up to 150 records)						
dial from call log	Settings / Applications					
	+ (1. Call History) + select a call log record					
	+ Press { All Calls } or { Missed }					
	Received - , Placed - , Missed - + { More } +					
	{ Edit Dial } to edit the displayed number if necessary + { Call }					
	/ lift the handset to start calling					
Personal Directory (Personal Phonebook)						
• sign in for Personal Phonebook	+ (4. Personal Phonebook) + { Select }					
	+ (2. Phone Directory) + { Submit }					
	Use the Navigation bar and button to scroll and select					
search for an entry	Open Personal Phonebook + { Search }					
	+ enter Search Criteria + { Submit }					
dial from entry	Search for an entry + { Select } + { Dial }					
. Up	Press up arrow key to review call history. Select a number to edit and					
Arrow	dial					
Keys Down	Press down arrow key to review the speed dial buttons, highlight the					
Down	stored speed dial, then lift up handset to dial					
Telephone Web Portal	Launch a web browser, & go to https://frsip.ust.hk/					
Totophone (to I orom	Login using 4-digit telephone extension no. and telephone web portal					
	password					
Contrast	Press + (2. Preferences)					
	+ (2. Contrast) + o adjust + { Save } to confirm					
Ring Tone	Press + (2. Preferences)					
	+ (1. Ring Tone) + to change +					
	select Ring Tone + { Play } to listen / { Set } + { Apply } to use					
Volume						
adjust the handset, headset and speaker volu	When handset, headset or speaker is in use (off hook), press:					
adjust the ringer volume	When handset, headset and speaker is not in use (on hook), press:					

	Buttons / Keys										
•	X		4	4		8	₿	ii .	+	×	
Handsfre Speaker	1	Hold	Transfer	Conference	Navigation (Up, Select, Down)	Voicemail	Settings / Application	Contacts	Volume Control	Forwarded icon	{} Softkey